

Accs. demand switch



- auxiliary relay for extension of the field disconnecter of the Nefa 16-plus F/1 series
- for controlling 3- phase appliances (electric cooker) or for switching off several circuits simultaneously
- The HR4S auxiliary relay is an extension of the NA 16-1P radio field disconnection switch to also switch off 3~ (400V) consumers, such as an electric cooker or several circuits simultaneously.
- The auxiliary relay HR4S is mounted next to the field disconnecter in the power distribution box and controlled by its output. Not suitable for automatic demand switches.

Order-No.: 720053
Short-Desc.: HR4S

Accessories Radio demand switch

Auxiliary relay HR4S

Technical data

| | |
|---------------------------|--|
| length: | 85 mm |
| width: | 35 mm (2 TE) |
| height: | 60 mm |
| colour: | light grey |
| control voltage: | 230 V |
| rated current: | 25 A |
| operating voltage: | 400 V |
| connection cross-section: | rigid (1 - 10 mm ²) flexible (1 - 6 mm ²) |
| switching contacts: | 4 NO contacts |
| approvals: | VDE DIN EN 61095 (VDE 0637-3) DIN VDE 0106-100 |
| other features: | hum-free screw technology |

Scope of application

extension for the field disconnecter of the series:
NA 16-1P Funk

Scope of delivery

auxiliary relay HR4S